



Visit product page

## IPA-50

L005749



Public Address mixer amplifier 50 w , 100V / 70V constant voltage output, 8 ohm constant resistance output, mp3, bluetooth, FM tuner ,USB interface,LCD screen, 3 line input, 2 mic input, 1 line output.Treble and Bass,IR control function

### TECHNICAL DETAILS

#### Technical Specifications

Rated power: 50W.

Mix input: -60 dB, 600Ω, unbalanced, 6.3 mm TS.

AUX input: -20 dB, 10 kΩ, unbalanced, stereo RCA jack.

Line output: 0dB, 600 Ω, unbalanced, stereo RCA jack.

Speaker output: High impedance 100V, 70V / low impedance: 8Ω.

Circuit protection: AC Fuse, overheating, overvoltage, overcurrent, short circuit, DC and delay protection.

Effects: 5 Equalizer presets can be selected for MP3 and FM.

Output control: Treble +/- 2dB @ 10 kHz, Bass +/- 12dB at 100 Hz.

Frequency response: 20 - 20 kHz (+/- 3 dB).

SNR: Mic input 66db, AUX input >75dB.

THD: <0.5% at 1kHz, when 1/3 ratepower output.

Power: 220 Volt, 50 Hz.

Power consumption: 70 Watt.

Net weight: 3.2 Kg.

Operation temperature / humidity: - 10°C, + 40°C, <95%.

Dimensions: 250 W x 72 H x 210 D mm.

Grossweight: 4 Kg.

Packing dimensions: 324 W x 110 H x 280 D mm.

# PHOTOS



# PRODUCT VIDEO

